Portable 2-Way Radio & FM Receive



Technical Datasheet

MTD90

performance is the ideal two-way radio with a convenient FM receiver built in. The MTD90 has 199 channels, FM radio, seven choices for back light colour, frequency space setting ctcss and dcs, battery saver, ani, dtmf with vox on/off and vox level setting. The MTD90 offers a busy channel lockout, scan with scan add and scan delete. Check and adjust the TX power level adjustment by easy hand operation, monitor, squelch level adjustment and tot function. LED display and setting for ease of use, keypad locked (manual/auto), different frequency function, emergency calling channel, offset, shift direct, channel named, memory channel settings, auto power off and wire clone for matching all units to

The MTD90 with its intelligent design, stability and high the same settings (optional).

Features:

- 199 Channels
- **VOX Hands Free**
- **DCS and CTCSS Indication**
- **FM Radio Receiver**
- 5, 7 and 9 Transmitter Power Indicator
- **LCD Display with 7 Backlit Colours**
- 34 Menu Options
- Sold as individual units

General Specifications

| Functions | Range |
|---------------------------------|-------------------------------------|
| Frequency Range | 136-174MHz, 400-470MHz |
| Channels | 199 |
| Channels Spacing | 5/6.25/10/12.5/25KHz |
| Working Voltage | DC 7.4V ± 20% |
| Dimensions | 114 x 57 x 38mm (without antenna) |
| Weight | 187.5g (without battery) |
| Accessories | Belt clip, charging unit & earpiece |
| Transmitter | |
| Output Power | 1W/4W |
| Modulation Mode | F3E/F2D |
| Clutter Radiation | ≤7.5uW |
| Adjacent Channel Power | 65dB |
| Frequency Deviation | ≤5KHz/2.5KHz |
| Audio Distortion | ≤5% |
| Frequency Stability | ±2.5ppm |
| Receiver | |
| Sensitivity (12Db SINAD) | 0.16uV |
| Modulation Receiver Bandwidth | ±7KHz / ±3.5KHz |
| Adjacent Channels Selectivity | 60dB |
| Intermediation Squelch Response | ≥60dB |
| SNR | ≥60dB |
| Frequency Stability | ≥60dB |
| Audio Output | ±2.5ppm |
| Distortion | 500mW |









LCD Display with 7 Backlit Colours

34 Menu Options

199 Channels

Optional Accessories:

- MTD90BATT: Spare Battery
- MTD90SP/MIC: Spare Mic
- MTD90CC: Cloning Cable



| Port Elizabeth | Bloemfontein







